



How to Reset an ER10 Error Code: Dri-Eaz® i-Series Dehumidifiers

An **ER10 error code** may occasionally appear on the Command Hub display of a Dri-Eaz i-Series dehumidifier. If an ER10 code is displayed and you have been instructed to reset the error, follow the steps below to access the service menu, clear the code and restart the unit.

This procedure applies to the following Dri-Eaz dehumidifiers equipped with the i-Series Command Hub controls:

- Revolution® LGR
- PHD 200
- LGR 3500i
- LGR 6000Li
- LGR 6500XLi
- LGR 7000XLi
- Syclone™ 145
- Syclone™ XL

Resetting an ER10 Error Code

1. Open the Menu

- From the Command Hub home screen, tap **Menu**.




2. Navigate to the Second Menu Screen

- Tap the **arrow button** to toggle to the second menu screen



3. Access the Service Menu

- On the second menu screen, **tap the bottom-right corner of the screen five (5) times.**



- **Important:** The additional icons shown in the example image below will **not** initially appear on your screen. At this point, you should only see the **Register Device** icon.

4. Enter the Password

- When prompted, enter: **4462**
- Then tap **OK**.

5. Open the Info Screen

- Tap **Info**.
- Then Tap **Reset ER10**.
- Once the reset is complete, **the red warning triangle in the header should disappear**, indicating that the ER10 error has been cleared.

6. Return Home and Restart the Unit

- Tap the **Home icon** to return to the main screen.
- Turn the dehumidifier **ON and** confirm that the unit begins operating normally.

If the ER10 Code Returns

If the ER10 error reappears after completing the reset procedure, the unit may require additional troubleshooting or service. Do not repeatedly reset an error that continues to return. Contact **Dri-Eaz / Legend Brands Technical Support** for assistance before continuing operation.

Quick Reference:

Menu → Second Screen → Tap Bottom-Right Corner 5× → Enter 4462 → Info → Reset ER10 → Home → Turn Unit